

Approximation of Gaussian derivatives for UWB communication

Harsh R. Jani¹ Khyati P. Vachhani²

¹ M.E. Student, ² Assistant Professor

^{1,2} Kalol Institute of Technology & Research Centre, Kalol

Abstract - UWB is a new interesting technology for wireless communications. It can replace traditionally carrier-based radio transmission by pulse-based transmission using ultrawide band frequency but at a very low energy. An important aspect of research in this domain is to find a pulse with an optimal shape, whose power spectral density respects and best fits emission limitation mask imposed by FCC. In this paper we review common used Gaussian pulses and its derivatives and the influence of shape factor, finding an optimal specific value for each derivative. Next, we search to obtain possible better pulse shapes as linear combinations of Gaussian derivatives. Older studies refer in one case to the same shape factor for all derivatives and in other case to higher factor for first derivative and smaller shape factors for subsequent derivatives.

Our new idea is to use Gaussian derivatives, each with its specific optimal shape factor and to use a "trial and error" algorithm to obtain a linear combination pulse with better performance.

Keywords: Gaussian Monocycle; Shape factor; Trial and error; UWB; FCC mask;

I. INTRODUCTION

UWB (Ultra-Wide-Band) wireless transmission is based on impulse radio and can provide very high data rates over short distances. Its traditional application was in non-cooperative radar. UWB device by definition has a bandwidth equal or greater than 20% of the center frequency or a bandwidth equal or more than 500MHz. Since FCC (Federal Communications Commission) authorized in 2002 the unlicensed use in the domain 3.1– 10.6 GHz, UWB became very interesting for commercial development. High data rate UWB can enable wireless monitors, efficient transfer of data between computer in a Personal Wireless Area Network, from digital camcorders, transfer of files among cell phone and home multimedia devices, and other radio data communication over short distances [7].

Traditional wireless technologies use radio sine waves that provide "continual" transmission at a specific frequency. UWB radio system is associated with its impulse-based, carrier-free, time-domain radio system format that transmits very short UWB pulse signal trains (sub-nanosecond pulse width) without using any continuous sinusoidal wave carriers. For pulse-based UWB system, an extremely short pulse spreads its signal power over a very wide frequency spectrum (3.1-10.6 GHz) where the duty cycle of UWB pulse train can be as low as 1% [3]. The pulses are emitted in a rhythm unique to each transmitter. The receiver must know the transmitter's rhythm signature or pulse sequence to "know how to listen" for the data being transmitted [5].

The study of the shape of base pulse is fundamental because on it depend the performances of an UWB system, like efficiently use of permitted emission power, coexistence with other radio communication systems and a simple circuit implementation.

One of the fundamental challenges is to maximize the radiated energy of the pulse while the power spectral density complies with the spectral FCC mask.

The FCC regulated the use of UWB devices respecting emission limit values as depicted in Fig.1 [4]. Due to the extremely low emission level currently allowed, comparable with unintended emission (FCC Part 15), UWB systems are suited for short-range and indoor applications. UWB operates best over short distance of about 2-3 meters delivering data speeds of 480 Mbps. As distance increases, speed decreases, but at 10 meters still reaches or exceeds 100 Mbps.

Since the ultra-short pulses are relatively easy to generate only with analog components, the Gaussian Monocycle and his derivatives are commonly used for UWB.




Figure-1: UWB indoor emission mask reglemented by FCC.

II. GAUSSIAN DERIVATIVES

By far the most popular pulse shapes discussed in UWB communication literature are the Gaussian pulse and its derivatives, as they are easy to describe and work with.

The basic Gaussian pulse is described analytically as:

$$x(t) = \frac{A}{\sqrt{2\pi\alpha}} e^{-\frac{t^2}{2\alpha^2}} \quad (1)$$

If a Gaussian pulse is transmitted, due to the derivative characteristics of the antenna, the output of the transmitter antenna can be modeled by the first derivative of the Gaussian pulse [1]. Therefore, the pulse radiated is given by

the first derivative of the Gaussian pulse, called a monocycle:

$$x^{(1)}(t) = \frac{A}{\sqrt{2\pi}\alpha^3} e^{-\frac{t^2}{2\alpha^2}} \quad (2)$$

The equation of n-th derivative pulse is given by:

$$x^n(t) = \frac{d^n}{dt^n} \left(\frac{A}{\sqrt{2\pi}\alpha} e^{-\frac{t^2}{2\alpha^2}} \right) \quad (3)$$

A UWB transmitted signal, using PAM, with uniformly spaced pulses in time can be represented as

$$s(t) = \sum_{k=-\infty}^{\infty} a_k x^{(n)}(t - kT) \quad (4)$$

where T is the pulse-spacing interval and the sequence {ak} represents the information symbol. The PSD of the transmitted signal, P(f)

$$P(f) = \frac{\sigma^2}{T} |X_n(f)|^2 + \frac{\mu a^2}{T^2} \sum_{k=-\infty}^{\infty} \left| X_n\left(\frac{k}{T}\right) \right|^2 \delta\left(f - \frac{k}{T}\right) \quad (5)$$

where $X_n(f)$ is the Fourier transform of the n-th derivative of a Gaussian pulse, σ^2 and μa are the variance and mean, respectively, of the symbol sequence { a_k }, and $\delta(\cdot)$ is the Dirac delta function. The second term in (5), composed of discrete spectral lines, will vanish if the information symbols have zero mean. In what follows, we assume this is true and also assume that $\sigma_a^2 = 1$. Strictly speaking, the duration of the Gaussian pulse and all of its derivatives is infinite. From the equation (3), we can find first 16 derivatives of Gaussian pulse for the value of $\alpha = 0.5$ ns. First sixteen derivatives can be shown as below in Figure-2.




Figure-2: First Sixteen derivatives of Gaussian pulse

III. APPROXIMATION OF SHAPE FACTORS

Here, our main task is to find the value of PSD that fits best with respect to FCC mask. The possibility for tuning PSD spectrum in order to respect and fit the mask FCC is the choice of the shape factor σ . We observe that decreasing the value of σ in time domain the duration of pulse T_p is shorter, and leads in frequency domain the spectrum to migrate to higher frequencies.

Results and analysis shows that, PSD Gaussian 5th order derivatives fits best w.r.t FCC emission mask.

Here, we take an example of Gaussian 5th order derivative by taking the value of shape factor 0.3ns and taking the step size of 0.001ns for 50 steps.




Figure-3: Approximation of 5th derivative Gaussian Pulse

We follow above procedure for first fifteen derivatives of Gaussian pulse and find the approximated value of shape factor by taking 50 steps for each derivative. Below table shows results for first fifteen derivatives.

Derivative order	Sigma app.(ns)	BW[10db](GHz)
1	0.033	7.50
2	0.039	7.50
3	0.044	7.40
4	0.047	7.07
5	0.051	6.64
6	0.053	6.19
7	0.057	5.59
8	0.060	5.57
9	0.062	5.48
10	0.064	5.24
11	0.067	5.08
12	0.069	4.94
13	0.071	4.79
14	0.073	4.66
15	0.075	4.54

Table-1: Approximate values for derivatives Gaussian pulse

These results show that the pulse width will be less than 1 nanosecond for all cases, and the 10dB bandwidth is 4.5 GHz or greater; peak frequency increases with square root of order of derivatives. The maximum PSD can be controlled by changing the value of the amplitude A of the pulse [8].

Note that the derivative operation could be implemented as highpass filtering; to transmit the fifth derivative over the air, the Gaussian pulse must be filtered to the fourth-order derivative [2].

IV. APPROXIMATED COMBINATION OF PULSES

In order to obtain UWB pulse with a better performance, we investigated linear combinations of Gaussian derivatives pulse. Let us consider a base pulses composed of first 15 derivatives of Gaussian pulse, each with an individual shape factor.

The combination pulse has the expression given by eq.(6).

$$x(t) = \sum_{n=1}^{15} c_n \cdot x^{(n)}(\sigma_n, t) \quad (6)$$

The problem is to find the optimal set of coefficients $S = \{c_n\}$, so that the resulting combination pulse respects and best fits FCC requirements [1]. We propose a computer-based method by means of starting with random sets of coefficients and testing with a 'trial-and-error' procedure described as follows.

- 1) Step 1. Initialize the random number generator.
- 2) Step 2. Generate a random set of coefficients S .
- 3) Step 3. Check if the PSD of the linear combination obtained with coefficients and base pulses satisfies the emission limits.
- 4) Step 4. If the emission limits are not met, go to step 2 and generate another combination.
- 5) Step 5. If the emission mask are met and this is the first set verifying the limits, initiate the optimal set $BS = S$
- 6) Step 6. If the emission mask is met and already exists an optimal set, compare actual valid set S with optimal set BS . If S have a better fit of a mask, i.e. the sum of PSD (expressed in mW/Hz) at all frequencies is greater, redefine $BS = S$.
- 7) Step 7. Repeat this procedure going to step 1 for some number of "trial" cycles, in order to obtain a new possible improved pulse.
- 8) Step 8. After that number of independent random searches (because in step 1 the random generator is reinitialized), algorithm stops and the current BS is the optimal found.

If one runs this algorithm for a sufficiently big number of "trials", the results converge and one obtains a best result possible.

We run this algorithm for three cases, as a function of choice of the set of shape factors σ_n of each based pulse for combination.

Case-1: The case of the same shape factor σ for all derivatives.




Figure-4: PSD for same shape factor

In this case we consider the pulses derivatives having same shape factor σ . The result for a value of $\sigma_n = 0.2\text{ns}$ is presented in Fig.4..

Case-2: The case of the different shape factor σ for all derivatives.

Improved performance can be achieved by adopting different values for component derivative pulses.

Consider a second set of a values characterized by a higher value of σ (0.42 ns) for the first derivative and smaller values (0.08 ns) for the higher derivatives [1].

The new values improve the performance of the trial-and-error procedure, leading to a PSD that is quite close to the target for frequencies up to about 8 GHz, as is depicted in Fig.5.




Figure-5: PSD for different shape factor

This PSD achieves a better approximation of the mask at higher frequencies than the continuous one, thanks to the larger bandwidth of higher derivatives.

Note that the selection of a relatively high a for the first derivative improves efficiency in power utilization at low frequencies.

An upper bound for a is given, however, by waveform duration, as determined by the chip time [1].

Case-3: The case of the different shape factor σ for all derivatives.

Regarding the discussion in Section 2, we propose the idea to consider as base pulses for the combination of Gaussian derivatives, pulses having its specific optimized shape factor σ_{opt} (cf. Table 1).

Applying optimization algorithm will result an optimal pulse combination with PSD presented in Figure-6.




Figure-6: PSD for approximated shape factor

As we see, this combination pulse has very good properties in fitting the mask and therefore using maximum allowed emission power.

For an objective comparison and correct performance evaluation of this pulse, in each figure is displayed the parameter used in algorithm "trial and error", PS, what is "Spectral Power" obtained summarizing numerical values of PSD (expressed in mW/Hz), at all sampled frequencies .

The value obtained here is the best, $PS = 2.73 \cdot 10^{-4}$ mW. In the case of using the same values for σ , the obtained value is poor $PS = 7.5 \cdot 10^{-6}$ mW and in case of higher σ for first derivative and smaller for higher order derivatives, PS is better, $PS = 1.99 \cdot 10^{-4}$ mW.

V. CONCLUSION

UWB technology is new and subject to more improvements. Signal pulses with duration of the order of ns are easy to generate using an analogue circuit. Gaussian monocycle and his derivatives is a commonly used waveform for pulses in UWB.

It is easy to generate, but does not have enough good performance. One of the problems is to obtain a PSD that better fits limited emission mask. Higher order derivatives have been studied and proved to bring better performance, but not enough.

Here, we try an algorithm to obtain a pulse from a linear combination of first 15 derivatives of the Gaussian pulse. Using this method with same shape factor for all derivatives, and next an old implementation with small values for monocycle and high values for higher derivatives leads to UWB pulses with PSD that respect and show improved fitting of the mask, but not enough good above 4, respectively 7 GHz.

We proposed the idea to use as base pulses for combination the Gaussian derivatives with σ values individually optimized by the criterion to obtain maximum bandwidth. With these pulses, the optimal combination obtained by a "trial and error" algorithm leads to a pulse with better performance that respects and better fit the mask. The diagram illustrates than theses pulses have a PSD well approximating the mask at all frequencies, therefore they efficiently use the available bandwidth and power.

The results for the new proposed pulses are interesting and subject to further theoretical analysis and practical implementations.

Numerical results and diagrams are obtained by means of a simulation program written by us in MATLAB.

REFERENCES

- [1] Maria-Gabriella Di Benedetto , Luca De Nardis, "Tuning UWB signals by pulse shaping: Towards context-aware wireless networks " , in Signal Processing 86 (2006)
- [2] D. Kn Hongsan Sheng, Philip Orlik, Alexander M. Haimovich, "On the Spectral and Power Requirements for Ultra-Wideband Transmission " , IEEE International Conference on Communications (ICC), 2003
- [3] Jin He and Y. P. Zhang, "A CMOS Differential Fifth Derivative Gaussian Pulse Generator For UWB

Applications", Microwave And Optical Technology Letters, Vol. 52, No. 8, pp.1849-1852, 2010.

- [4] Federal Communications Commission, "Revision of Part 15 of the commission's rules regarding ultra-wideband transmission systems, First Report and Order. February 14, 2002."
- [5] <http://www.wisegeek.com/what-is-uwb.htm>
- [6] http://www.qmitw.com/home_tech.html
- [7] B. Hu, N. C. Beaulieu, "Pulse Shapes for Ultrawideband Communication Systems," IEEE Trans., July 2005
- [8] Oppermann I., Hämäläinen M., Iinatti J.: UWB Theory and Applications, Wiley, 2004
- [9] M. Ghavami, L. Michael, R. Kohno, "Ultra Wideband Signals and Systems in Communication Engineering", Wiley, 2004.
- [10] Xiliang Luo, Liuqing Yang, and Georgios B. Giannakis," Designing Optimal Pulse-Shapers for Ultra-Wideband Radios", JOURNAL OF COMMUNICATIONS AND NETWORKS, VOL. 5, NO. 4, DECEMBER 2003.